
HDMR-54

Audio/Video Receiver 5.4 GHz

This is a special audio/video receiver with an LCD screen 4.3" for 5.4 GHz Fully synthesized this receiver has an SMA connector for different type of antennas for 5.4 GHz. This receiver has 8 preprogrammed channels. This receiver has built-in low noise preamplifier 12 dB gain for 5.4-5.9 GHz band.

Dimensions: 4.45 " X 3.6 " X 1.2 " .



Technical Specifications	
BATTERY POWERED	12 V
CURRENT CONSUMPTION	455 mA
DEMODULATION	WFM
SENSITIVITY	-86 dBm
ANTENNA CONNECTOR	SMA
FREQUENCY:	5.4 GHz
VIDEO OUTPUT	1V
AUDIO OUTPUT	300 mV
POLARITY PROTECTED	YES
PLL (PHASE LOOKED LOOP)	YES
TEMPERATURE RANGE:	-20+70°C
NUMBER OF CHANNELS	8 INTERNALLY SELECTED
DIMENSIONS	4.45" X 3.6" X 1.2"
VIEWING SCREEN:	4.3"