
VRX-58LC

Audio/Video Receiver 5.8 GHz

This is the most sensitive and definitely the best 5.8 GHz Video receiver on the market. Fully synthesized this receiver has an SMA connector for different type of antennas for 5.8 GHz. This receiver is full tunable in 5,65 GHz – 6,00 GHz range



Technical Specifications	
BATTERY POWERED	5 V
CURRENT CONSUMPTION	395 mA
DEMODULATION	WFM
SENSITIVITY	-86 dBm
ANTENNA CONNECTOR	SMA
VIDEO INVERSE FUNCTION	N/A
VIDEO OUTPUT	1V
AUDIO OUTPUT	300 mV
POLARITY PROTECTED	YES
PLL (PHASE LOOKED LOOP)	YES
TEMPERATURE RANGE:	-20+70°C
NUMBER OF CHANNELS	FULL RANGE TUNABLE
DIMENSIONS	3" X 3" X 1"