



VRX-58LZ

Audio/Video Receiver

5.4- 6 GHz

This special microwave audio-video receiver covers all frequencies from 5.4 GHz – 5.96 GHz by using dip switches. Fully synthesized this receiver has an SMA connector for different type of antennas for 5.4 GHz – 5.9 GHz band. This receiver has over 30 channels.



AUDIO 1 AUDIO 2 VIDEO POWER

ANTENNA

Technical Specifications	
Operating Frequencies:	5450-5960 MHz
Channels:	Dip switches
DC Voltage:	9 V – 12 V
Sensitivity:	-88 dBm
Minimum required voltage:	10 V
Battery power:	12 V
Video distortion:	3%
Maximum range:	N/A
Video Format:	PAL, NTSC
Current Consumption:	350 mA / 12 V
Antenna:	N/A
Antenna Connector:	SMA
Impedance:	50 ohms
Audio outputs:	300 mV
Video/Audio Connectors:	RCA F
Video Impedance:	75 ohms
Video level:	1 V
Temperature Range:	-10 +65 °C
Dimensions:	5.6" X 2.5" X 0.8"
Weight:	100 grams
Demodulation:	WFM