



VRX-2000M 1900 – 2100 MHz VIDEO RECEIVER WITH TUNABLE FUNCTION

This small receiver will give you opportunity to monitor 1.9 GHz video band. Simply hook-up this receiver to any video monitor. It is fully portable, extremely sensitive and easy to use. You can get any frequency in 1900 - 2100 MHz band by turning super precision multi turn potentiometer. This receiver has built-in a special AFT (Automatic frequency tuning) control function for the best stability.
Dimensions: 4.3 " X 2.8 " X 1.0 ".



Technical Specifications	
Battery power:	12 V
Connector:	SMA
Audio output:	300 mV
Video output:	1 V
Video Format:	NTSC or PAL
Current Consumption:	395 mA
Sensitivity:	-86 dBm
Frequency demodulation:	Yes
Polarity protected:	Yes
Digital controlled:	Yes
Dimension:	4.3"x2.8"x1.0"
Frequency coverage:	1.9 GHz- 2.1 GHz