

VRX-58 Audio/Video Receiver 5.8 GHz

This small receiver is definitely the best 5.8 GHz Video receiver on the market. Fully synthesized this receiver has an SMA connector for different type of antennas for 5.8 GHz. This receiver is tunable™ and it covers all frequencies in 5.8 GHz band. Receiver VRX-58 also has a special Video inverse function. This receiver can access any video TV transmitter in 5.8 GHz band.



Technical Specifications	
Operating Frequency:	5700 MHz – 5900 MHz
Channels:	Tunable from 5.7 GHz- 5.9 GHz
DC Voltage:	9 V – 12 V
Sensitivity:	-86 dBm
Minimum required voltage:	10 V
Battery power:	12 V
Video distortion:	3%
Audio carriers:	6 MHz, 6.5 MHz
Video Format:	PAL, NTSC
Current Consumption:	350 mA / 12 V
Antenna:	High-gain recommended
Antenna Connector:	SMA
Impedance:	50 ohms
Audio input:	300 mV
Video/Audio Connectors:	RCA F
Video Impedance:	75 ohms
Video level:	1 V
Temperature Range:	-40 +78 °C
Dimensions:	4.3" X 2.8 " X 1.0"
Weight:	100 grams
Demodulation:	WFM