



VRX-24

8 Channels Audio/Video Receiver

2.4 GHz

This is the smallest video receiver on the market for 2,4 GHz with amazing sensitivity and easy to use. It is fully synthesized and built in a small plastic case size 3" X 3" X 1". This receiver has 8 selectable channels. It works from 10 V- 14 V DC. This is a special design for the specific application where the size and quality is the main factor. Video out is 1 V / 75 ohm. This receiver doesn't have an audio portion. This unit complies all FCC standards! High gain antenna can be connected via an SMA connector for the best performances and range.



Technical Specifications	
BATTERY POWERED	7 V - 12 V
VIDEO OUTPUT	1V
CURRENT CONSUMPTION	180 mA
AUDIO	N/A
FREQUENCY DEMODULATION	WFM
TV SYSTEMS	PAL OR NTSC
SENSITIVITY	-92 dBm
TUNABLE BAND	2.3 GHz - 2.5 GHz
ANTENNA CONNECTOR	SMA
DIMENSIONS	3.0" X 1.0" X 3.0"
NUMBER OF CHANNELS	8