



---

# LNAMP-1214

## SPECIAL LOW NOISE AMPLIFIER

### FOR 1200-1400 MHz RECEIVERS

---

This is an excellent small amplifier for 1.2-1.4 GHz receiver (not for transmitters). It will increase a gain of your receiver without adding large antennas. You can connect any 1.2-1.4 GHz antennas to input connector. This low noise amplifier will give you an extra 32 dB gain in 1.2-1.4 GHz band. The output connector is a male SMA type.



Applications:

- Analog and digital transmission systems
- Laboratory and test equipment
- Radar receivers

Technical Specifications	
Operating Frequency:	1200 MHz- 1400 MHz
DC Voltage:	+ 12 V
Gain	32 dB
Input Power	Max. 1 mW
Noise factor:	<0.6 dB
Maximum range:	N/A
Out IP3:	typ. +29 dBm @ 1300 MHz
Current consumption:	100 mA
Antenna Connector:	SMA
Impedance:	50 ohms
Temperature Range:	55 °C
Dimensions:	2.8"x 1.5" x 0.75"
Weight:	58 grams
Band-pass filter:	Built-in
Protection:	Reverse polarity