

AMP900-15 15 W 900 MHz AMPLIFIER MODULE

This is a high quality professional 15 W linear amplifier that requires minimum driving input of only 1 m W for the maximum of 15 W RF power output in 900 MHz range. This amplifier is linear and doesn't require any tuning or adjusting. Power supply is $12\ V/\ 2.6\ A$. Gain is 30 dB. Input / Output impedance 50 ohms. This amplifier has builtin band pass filter for 900 MHz band.



This unit is great for experiments, video surveillance or mobile radio applications.

Dimensions: 3.0" X 1.75".

| Technical Specifications | |
|--------------------------|-------------------|
| Operating Frequency | 890 MHz – 928 MHz |
| Operating Class | Linear AB |
| DC Voltage | 12 V |
| RF Power | 15 W |
| Input Power | 1 mW |
| Minimum required voltage | 10 V |
| Battery Power | 12 V |
| Video distortion | N/A |
| Video format | N/A |
| Current consumption | 2.5 A/ 12 V |
| Antenna | N/A |
| Antenna Connector | N/A |
| Impedance | 50 ohms |
| Temperature Range | -40+75 C |
| Dimensions | 3"x1.75" |
| Weight | 100 grams |