



BP 47-86 BAND PASS FILTER UHF 470 MHz – 860 MHz

This is a high quality band-pass TV UHF filter for 470 MHz- 860 MHz band. This filter is fully tunable and you can choose any TV channel from 14-69 NTSC or 21-61 PAL TV system.



Technical Specifications	
Operating Frequencies:	470 MHz-860 MHz
Maximum power:	600 W
Minimum channel spacing:	3 channels
Insertion loss:	<3 dB
Channel isolation:	>30 dB
Connectors:	N female
Impedance:	50 ohms
Temperature Range:	-10 + 75 °C
Dimensions:	5.5" x 2.8" X 1"
TV channels:	21-61 PAL, 14-69 NTSC
Channel Bandwidth:	+6 MHz

FILTER BP47-86

