



KF-300 FM AMPLIFIER 300 W FOR 88 MHz- 108 MHz



A highest efficiency and most reliable amplifier for 88 MHz- 108 MHz in the world! No maintenance required, just plug and play. Full 300 W RF Power /50 ohm antenna. This is a broadband amplifier- no tuning needed, only 10 W input power for the max. output 320 W.

Technical Specifications	
Operating Frequencies:	88 MHz- 108 MHz
Maximum output power	320 W
Input power	10W
Input connector	N type
Output connector	N type
Power consumption	410 VA
Impedence	50 ohms
Power stability	< 1%
RF efficiency	80% typ.
Temperature range	-5° C to + 45° C
Weight	22 kg
Dimensions	483 x 640 x 132 mm
Operating Voltage:	110/220/240 Vac ± 10% Vac 50/60 Hz, single-phase

Copyright © 2001-2008 RF-LINKS