



LX-900B/12

Audio/Video Transmitter

900 MHz 12 Channels

This video transmitter for 900 MHz has 12 selectable channels and it is excellent solution for video surveillance or experiments. The transmitter LX-900B/12 has 1.8 W RF power. Size of this transmitter is 5" X 4" X 1.2"....Recommended receiver is RM-900B.



900 MHz FREQUENCY CHANNEL LIST:

CH 01. 892 MHz	CH 02. 898 MHz
CH 03. 900 MHz	CH 04. 902 MHz
CH 05. 903 MHz	CH 06. 906 MHz
CH 07. 908 MHz	CH 08. 910 MHz
CH 09. 912 MHz	CH 10. 915 MHz
CH 11. 916.65 MHz	CH 12. 918 MHz

Technical Specifications	
Operating Frequencies:	900 MHz band
Channel:	# 12 SELECTABLE CHANNELS
DC Voltage:	12 V – 14.4 V
RF power:	1800 mW
Minimum required voltage:	9 V
Battery power:	12 V
Video distortion:	2%
Maximum range:	3000 ft los +
Video Format:	PAL, NTSC
Current Consumption:	1,200 mA / 12 V
Audio input:	300 mV
Antenna Connector:	BNC
Impedance:	50 ohms
Video Connector:	RCA F
Video Impedance:	75 ohms
Video level:	1 V
Temperature Range:	-20 +75* C
Dimensions:	5.0" X 4.0 " X 1.2"
Weight:	250 grams
Modulation:	Negative AM