



MX-50 SERIES MEDIUM POWER VIDEO SENDER

RF-links.com. introduces small Video senders for TV production and Film. Model MX-50 has 50 mW RF power and it is excellent low cost solution for Steadicam operators. Matching antenna is included. This unit is available in many different TV UHF channels. Dimensions: 2.2"x 1.5"x 0.8".

Available UHF Channels:

CH-59(cable), CH-15, CH-17, CH-18, CH-20, CH-22, CH-24, CH-26, CH-28, CH-30, CH-32, CH-34 UHF TV band



Technical Specifications	
SIZE:	2.4" X 1.5" X 0.7"
MAXIMUM OPERATING VOLTAGE	20V
RF POWER	50 mW
CURRENT CONSUMPTION	48 mA/ 12 V
ANTENNA CONNECTOR	BNC
UHF CHANNELS	15, 17, 18, 20, 22, 24, 26, 28, 30, 32, 33, 34
POWER SUPPLY	9 V - 12 V
VIDEO INPUT	1V/ 75 OHM
RANGE	Up to 300 ft under ideal conditions
POLARITY PROTECTED	YES